

BENKO PRODUCTS 05-08-2006

TEMPERATURE CONTROLLER REPLACEMENT

USE THE CHART BELOW TO MOVE WIRES

PARTLOW TERMINAL	FUTURE DESIGNS
# 9 - LINE	# 6 - LINE
# 10 - NEUTRAL	# 7 - NEUTRAL
# 2 - RELAY COMMON	# 8 - RELAY COMMON
# 1 - RELAY N/O	# 9 - RELAY N/O
# 4 - T/C RED WIRE (-)	# 4 - T/C RED WIRE (-)
# 5 - T/C WHITE (+)	# 5 - T/C WHITE (+)

The numbers in the chart are terminal numbers not wire numbers

This chart works when replacing a PARTLOW MIC-1160
With a FUTURE DESIGNS FDC-9090

These instructions will work with most of the older Benko Products control systems with standard options. Without reviewing an exact copy of the original schematic no guarantee can be made that following these instructions will work.